

Monofazni korektori napona velike snage serije MFDK



Karakteristike:

- > Servo motor regulator sa torusnim transformatorom i numeričkim displejom
- > Tip: MFDK 10k, MFDK 15k, MFDK 20k, MFDK 30k
- > Snaga: od 10kVA do 30kVA
- > Ulazni napon: 140 ~ 250V / 50Hz
- > Izlazni napon: 220V ± 2%

Tip	MFDK 10k	MFDK 15k	MFDK 20k	MFDK 30k
Snaga	10kVA	15kVA	20kVA	30kVA
Ulazni napon	140 ~ 250V / 50Hz			
Izlazni napon	220V ± 2%			
Dimenzije (cm)	440x342x390	440x342x390	440x342x540	440x342x540
Težina (kg)	40	50	71	80

MARTINpower